

POWER PROTECTION

OFFICE-LITE 2000

Plug-and-play protection for sensitive electronic equipment. Available in three outlets and various socket options. The office-Lite 2000 automatically disconnects the power to the equipment in the event of damage to the protection element or power overload. Suitable for electronic and electrical equipment.. This unit has an on/off switch incorporating a circuit breaker and power on indicator. EMI/RFI filtration has been included.



- Easy installation
- Surge protection and filtration
- Failsafe protection
- Economical protection solution

TECHNICAL SPECIFICATIONS

Max. continuous voltage	275V / 50Hz
Max. continuous current	15A
Earth leakage	< 1.5mA
Max. discharge current (8/20)	8kA
Response time	< 25ns
Filtration at 100KHz	50 db
Standards compliance	IEC 99.4, IEC 950, IEC 61643-1

ORDER CODES

U.K.	GERMANY	S.A.
12-00037	12-00839	12-00822

We reserve the right to change specifications without prior notice

Cat/officelite2000

Tel: (011) 886- 7874

Fax: (011) 787-0178

Email: sales@sinetech.co.za